

# METHOD AND APPARATUS FOR REMOVING A MATERIAL LAYER FROM A SUBSTRATE

Inventors: Yakov Epshteyn  
Sumit Guha  
Yehiel Gotkis  
William J. Bellamak

## Cross-References to Related Applications

<sup>10</sup> ~~This application is a continuation in part of U.S. Serial No. 09/415,898 filed on October 8, 1999, and of common assignee.~~

## Field of the Invention

The present invention relates to integrated circuit manufacturing technology, and more particularly, to buff systems typically used in conjunction with chemical-mechanical polishing of semiconductor wafers. Still more particularly, the present invention relates to a method for removing a barrier layer from a substrate to improve processing time and polishing quality.

## Background of the Invention

Currently, various photolithographic optics-based processes are used in the manufacture of integrated circuits on semiconductor wafers. Because these optics-based processes generally require accurate focusing in order to produce a precise image, the surface planarity of the wafer is an important issue.

There are several techniques for planarizing the surface of a semiconductor wafer. One technique is chemical-mechanical polishing (CMP). A standard CMP tool is shown in Figure 14. These tools generally include a carrier 403 to mount a wafer 12 and a polish pad 404 supported by a polishing platen 406. The CMP tool 401 causes the polish pad 404 and the wafer 12 surface to come into contact, typically applying a specified pressure between the polish pad 404 and the wafer 12 surface. The CMP tool 401 also imparts a relative motion between the wafer 12 surface and the polish pad 404 by orbiting or rotating the polishing pad about an axis and/or rotating the wafer carrier 403. In addition, the CMP tool typically introduces slurry 405 at the interface between the polishing pad 404 and the wafer surface 12. The slurry 405 can have abrasive particles suspended in a chemical solution that reacts with selected materials on the wafer 12 surface. The pressure, slurry and relative motion effectuate the polishing. After polishing, a secondary buff step is often used to remove microscratches and strongly adhering particles and to provide a final light polish. After buffing, the wafers 12

go through a clean up and drying process to remove residual slurry, metal particles, and other potential contaminants from its surface.

Integrated circuits manufactured today are made up of literally millions of active devices such as transistors and capacitors formed in a semiconductor wafer. Integrated circuits rely upon an elaborate system of metalization in order to connect the active devices into functional circuits. A typical multilevel interconnect 12 is shown in FIGURE 12d. Active devices such as MOS transistors 107 are formed in and on a silicon substrate or well 102. An interlayer dielectric (ILD) 104, such as  $\text{SiO}_2$ , is formed over silicon substrate 102. ILD 104 is used to electrically isolate a first level of metalization which is typically aluminum (Al), or copper (Cu), from the active devices formed in substrate 102. Metalized contacts or vias 106 electrically couple active devices formed in substrate 102 to interconnections 108 of the first level of metalization. In a similar manner contacts 106 electrically couple interconnections 114 of a second level of metalization to interconnections 108 of the first level of metalization. Contacts 106 typically comprise a metal 116 such as tungsten (W) surrounded by a barrier metal 118. Additional ILD/contact 106 and metalization layers can be stacked one upon the other to achieve the desired interconnections.

Most metal structures are formed on a wafer with a barrier layer deposited underneath so as to act as an adhesion layer to provide low electrical resistance and prevent diffusion of the metal into the dielectric layer. Common barrier layers used in integrated circuit manufacturing are titanium (Ti), titanium nitride (TiN), and tantalum (Ta). The barrier layers have very different chemical and physical properties than the top metal layer which is typically comprised of tungsten, aluminum, or copper. Accordingly, the polishing behavior of the barrier layers can be quite different than their respective top metal layers. Applicants have noticed that to maximize the efficiency of the planarization process, both the polishing slurry and pad configuration need to be compatible with the material being polished.

A common practice in semiconductor manufacturing is the formation of metal plugs, typically tungsten plugs, which serve as contacts and vias between two layers of metal. As above, barrier layers comprising Ti, TiN, Ta, or a combination of these are commonly inserted between the underlying dielectric layer and the plug metal to aid in adhesion and reduce diffusion of the plug metal into the underlying dielectric layer. Due to the chemical properties which may be chosen for use in slurry, most commercially available tungsten polishing slurries can polish a tungsten film with at least 3 to 10 times higher removal rate than polishing Ti. For this reason, the slurry composition is typically changed between the steps of removing a metal

layer and a barrier layer. Thus, a further disadvantage that occurs in a conventional CMP process is the interaction between multiple slurries of differing chemical composition when used on the same polishing pad.

Typically, both the metal and barrier layers are removed on the same polish pad in the presence of one or more slurry compositions. However, Applicant discovered that removing both the metal and barrier layers on the same polish pad creates various problems for the process, depending on the materials being planarized. For example, when copper is planarized, a multi-step process is used in which the slurry is changed and the polish pad conditioned between removal of the metal layer and removal of the barrier layer. Typically, to avoid any unwanted interaction between different slurries, deionized water is used to rinse the first slurry before a second slurry is applied to the primary polish station. This rinsing process may take several seconds which increases processing time. Even after rinsing, residual amounts of the first slurry may remain on the polish pad which might introduce the possibility of reacting with either the second slurry or the material being planarized..

In another example, when tungsten is planarized in a CMP tool, there is only one slurry used for removing both the tungsten and barrier layers. Using a conventional system, however, both layers are still removed on the same polish pad. The slurry used is chemically reactive to tungsten and therefore, a certain amount of undesirable tungsten erosion in the plug and/or metal structures can occur when removing the barrier layer. Also, the down-force exerted on the wafer during polishing at a primary polishing station is typically about 4 psi which reduces the planarity of the wafer surface as compared to a lower pressure, and thus creates the possibility of creating undesired open or closed circuits within the wafer.

What is needed is a method for removing the barrier layer from the front surface of a wafer without the undesired side effects associated with removal of the barrier layer on the same polish pad as the metal layer.

### Summary of the Invention

In accordance with aspects of the present invention, an improvement is provided to chemical-mechanical polishing machines. The improvement includes using a buffing pad having a geometrically optimized shape, along with an optimized configuration of the offset  $O$  and the overlay  $L$  (which is a function of the buff head diameter and the offset). In one embodiment, the pad is circular but mounted to the buff head eccentrically. In another

embodiment, the buffing pad has a generally square outer shape. In another embodiment, the buffing pad has at least three radially extending arms.

In another aspect of the present invention, the optimal configuration is determined iteratively for a selected process by changing the offset, overlay, buff head diameter and pad shape. For example, increasing the offset tends to increase the removal rate toward the edge of the wafer (in general). Increasing the overlap generally tends to increase the removal rate in the center of the wafer.

Besides changing the offset, overlap and buff head diameter, the shape of the pad itself can be modified to tailor the removal rate profile. Typically, the desired removal rate profile is as uniform as possible. In the embodiments of the present invention described herein, the removal characteristics of the system were optimized to balance the removal rate between the edge and the center. However, when optimizing only the overlap, offset and buff head diameter, the resulting removal rate profile was both edge and center fast. To further increase the uniformity of the removal rate profile, pad material was removed near the edge of the buff head so that the removal rate would decrease at both the edge and the center. This produced a significant improvement in uniformity. The best pad shape tested so far is a round pad smaller than the buff head (86% in diameter) and mounted to the buff head eccentrically and tangent at one point on its edge.

The present invention further provides a method and apparatus for planarizing a front surface of a wafer. The invention improves the planarization process by providing a method and apparatus for removal of a first material layer on a main polish station, and removal of a second material layer, preferably a barrier layer, on a buff station.

### **Brief Description of the Drawings**

The foregoing aspects and many of the attendant advantages of this invention will become more readily appreciated as the same become better understood by reference to the following detailed description, when taken in conjunction with the accompanying drawings, wherein:

FIGURE 1 is a simplified perspective view of a conventional buffing system.

FIGURE 2 is a plan view illustrating the parameters overlay and offset of FIGURE 1.

FIGURE 3 is a scaled plan view illustrating the standard buffing unit configuration.

FIGURE 4 is a diagram illustrating the removal rate profile obtained using the buffing unit configuration of FIGURE 3 and illustrates the inherent center fast property of a conventional configuration.

FIGURE 5 is a scaled plan view of a first test configuration.

5 FIGURE 6 is a scaled plan view of a second test configuration.

FIGURE 7 is a diagram illustrating the resulting removal rate profile obtained by using the configuration of FIGURE 5 and illustrates that the increased offset and pad size cause an edge fast removal rate profile.

10 FIGURE 8 is a diagram illustrating the resulting removal rate profile obtained by using the configuration of FIGURE 6 and illustrates the achieved balance between being edge fast and center fast.

FIGURE 9 is a plan view illustrating a first embodiment of a buffing pad with a generally square shape.

15 FIGURE 10 is a diagram illustrating the removal rate profile obtained by using the configuration of FIGURE 6 in conjunction with the pad shape of FIGURE 9.

FIGURES 11A-11H are plan views illustrating various embodiments of a buffing pad formed in accordance with the present invention.

FIGURE 12a is a cross section of a standard wafer before etching.

20 FIGURE 12b is a cross section of a standard wafer after etching and before barrier layer deposition.

FIGURE 12c is a cross section of a standard wafer after barrier layer deposition and before plug metal deposition.

FIGURE 12d is a cross section of a standard wafer after plug metal deposition.

25 FIGURE 12e is a cross section of a standard wafer after planarization of the plug metal and before barrier layer planarization.

FIGURE 12f is a cross section of a standard wafer after barrier layer removal.

FIGURE 12g is a cross section of a standard wafer after metal interconnects have been added.

FIGURE 12h is a cross section of a typical multilayer interconnect.

FIGURE 13 is a cross section of an embodiment of the present invention.

30 FIGURE 14 is a cross section of a standard primary polish station.

FIGURE 15 is a diagram of one possible process for the invention.

### **Detailed Description of the Preferred Embodiment**

The present invention is an improvement to chemical-mechanical planarization equipment and methodology. The improvement can be applied to both buffing systems and primary polishing systems. The improvement includes using a buffing pad with a geometrically optimized shape and an optimized configuration of the offset  $O$ , overlay  $L$ , and buff head diameter, referred to herein as parameters.

FIGURE 1 illustrates a known buff system 10 used to buff a wafer 12. In this example, buff system 10 is part of a 776 polisher, available from SpeedFam-IPEC Corp., Chandler, Arizona. Buff system 10 includes an arm 13; a buff head 14 with a polish pad 20 mounted thereon, a platen 16 with polish pad 21 mounted thereon, and roller supports 18. The roller supports 18 help hold the wafer 12 prior to buffing and also prevent lateral movement of the wafer 12 during buffing. During the buffing process, platen 16 moves upward to contact wafer 12, while buff head 14 moves downward to contact wafer 12 and apply a selected downforce. Buff head 14 and platen 16 then rotate, causing wafer 12 to rotate, thereby buffing the surface of wafer 12.

In this system, the buff head 14 has a diameter that is less than the diameter of wafer 12. The relative placement of buff head 14 and wafer 12 is illustrated in FIGURE 2. During the buff process, the center of buff head 14 is offset from the center of wafer 12 by a distance  $O$  (referred to as the offset), with buff head 14 "overlapping" the center of wafer 12 by a distance  $L$  referred to herein as the overlay or overlap.

In a standard configuration (adapted for wafers 200mm in diameter) of the aforementioned 776 buff system, the buff head is approximately 4.50 inches in diameter, with  $O$  being 4.43 cm (1.828 inches) and  $L$  being 1.067 cm (0.420 inches). This configuration is illustrated in FIGURE 3. In this standard configuration, buff head 14 and lower platen 16 are rotated at approximately 300 rpm. The wafer 12 rotates at about 50 rpm due to friction and the offset of the system. With the conventional system, the removal rate profile illustrated in FIGURE 4 is produced. This system achieved a non-uniformity of material removal from the wafer surface of about 60-70%. However, the ability to achieve a substantially planar wafer surface is preferred for removal of a material layer from the wafer surface at a buff station. The optimization of the buff station parameters as described below allows for the ability to effectively remove a material layer from the wafer surface.

Referring still to FIGURE 4, the removal rate profile obtained using a standard buff configuration is center fast, meaning that more material is removed from the center of the wafer

12 than from the edge. The variation achieved in wafer 12 surface topography from before and after buffing is fairly significant, on the order of 375 angstroms.

Figure 10 is a profile across the surface of a wafer 12 test structure to evaluate the planarity of the wafer 12 surface with an optimized buffing process in accordance with the present invention. As shown on the vertical axis, the degree of relative variation in wafer 12 surface material removal rate from before and after buffing is significantly decreased to approximately 100 angstroms, or about 10-15% nonuniformity. Applicants have discovered that the buffing process may be optimized to substantially improve the overall planarization process of the wafer 12. This improvement, in turn, allows for not only the removal of particulates and microscratches, but also for removal of a material layer, preferably the barrier layer 118 from the wafer 12 surface at the buff station 10.

The inventors herein have observed that the removal rate across a wafer 12 (i.e., removal rate profile) is dependent on the diameter of the buff head, the shape of the buff pad, the offset O and the overlay L. The inventors have observed that changing the buff head 14 diameter, buff pad 20 shape, offset O, and/or the overlay L alters the removal rate profile. These parameters affect the integrated relative velocity distribution (between a region of the wafer 12 and the portion of the buff pad 20 contacting that region of the wafer), as well as dwell time under the buff pad 20. Thus, by appropriately changing these parameters, the removal rate profile can be controlled. As used herein, the integrated relative velocity distribution refers to an area integration of the relative velocity due to the buff pad 20 rotation with respect to a rotating coordinate system fixed to the wafer 12 surface. The result of integrating the relative velocity is an integrated distribution that is a function of the distance from the center of the wafer 12. The integrated distribution is significant because the relative velocity distribution is one indicator of the relative material removal rate at a given point on the wafer 12. The integrated distribution does not take into account other factors such as the interaction of chemicals and liquid abrasives (slurries) and the distribution of these agents.

FIGURES 5 and 6 are schematic plan views illustrating different buffing unit configurations. The configuration of FIGURE 5 uses a larger buffing pad than the configuration of FIGURE 3, increases the offset, and decreases the overlap. The configuration of FIGURE 6 uses a larger buffing pad and offset than the configuration of FIGURE 3 but smaller than that of FIGURE 5, while decreasing the overlap compared to the configuration of FIGURE 3 but not as much as in the configuration of FIGURE 5. Table 1 summarizes the

offsets, overlaps, buff head diameter, removal rate profile characteristics, pad shape and standard deviation of the removal rate over the wafer diameter.

Table 1. Configuration Results Summary

Configuration	Offset (in)	Overlap (in)	Buff Head Diameter (in)	Buff Pad Shape	Standard Deviation
Original Fig 3	1.828	.420	4.50	Round	52%
Figure 5	2.917	.084	6.00	Round	71%
Figure 6	2.442	.310	5.50	Round	24%
Figure 6	2.442	.310	5.50	Square (4.06" side)	10.2%
Figure 6	2.442	.310	5.50	4.75" diameter eccentric	10.1%

The resulting removal rates profiles of the configurations of FIGURES 5 and 6 are shown in FIGURES 7 and 8, respectively. As can be seen, FIGURES 7 and 8 show that the removal rate profiles for the configurations of FIGURES 5 and 6 are "edge fast" and "center fast and edge fast", respectively.

One of the reasons that the configuration of FIGURE 5 is edge fast is that the edge of the wafer has a relatively large dwell time under the buffing pad because the edge of the wafer is aligned near the center of the buffing pad. As a result, the wafer edge is in contact with the buffing pad for a longer duration (dwell time). In contrast, in the standard configuration (FIGURE 3), the edge of the wafer is aligned near the edge of the buffing pad resulting in the wafer edge having a relatively low dwell time. Further, the wafer edge moves in more nearly the same direction as the buffing pad, thereby reducing the relative velocity difference, thereby reducing removal rate. The removal rate near the center of the wafer is relatively high for the conventional configuration due to the 100% dwell time and the high integrated velocity distribution. This creates the undesirable property of a highly non-uniform removal rate profile.

On the other hand, the configuration of FIGURE 6 is both edge fast and center fast (see the associated removal rate profile of FIGURE 8). The offset in this configuration causes the wafer edge to be aligned fairly near the center of the buffing pad, which increases the dwell time of the wafer edge. However, because the offset and the buff pad are smaller in this configuration compared to the configuration of FIGURE 5, the removal rate at the wafer edge



is slightly lower. Thus, this configuration demonstrates a balance between being edge fast and center fast.

Once an optimal offset and overlap configuration is achieved, the inventors appreciated that further improvements in the uniformity of the removal rate profile can be realized by changing the shape of the pad on the polish head. In one embodiment, pad material is removed from the outer portion of the polish pad to decrease the removal rate at both the edge and the center of the wafer, thereby improving the removal rate uniformity of the system.

Although the removal rate profiles of FIGURES 4, 7 and 8 may be desirable in certain applications, in general, a uniform removal rate profile is desired. The inventors appreciated that appropriate shaping of the buffing pad can improve the uniformity of the removal rate profile.

FIGURE 9 illustrates a first embodiment of a buffing pad 18 formed in accordance with the present invention. The shape is essentially that of a square with portions of the squares corners clipped or rounded. In the embodiment shown in FIGURE 9, the pad has a side length, S, in the range of about 9.9 cm to about 10.6 cm, with one particular embodiment having a length of about 10.3 cm (~ 4.06 inches) with the corners rounded to match the buff head diameter. In this case, the square is not completely inscribed within the circular buff head, but instead has the rounded corners as shown in FIGURE 9. In light of the present disclosure, those skilled in the art will appreciate that the size of the square will vary depending on the diameter of the wafer being processed.

FIGURE 10 is a diagram illustrating the removal rate profile obtained using the buffing pad of FIGURE 9. As can be seen in FIGURE 10, the removal rate profile is significantly more uniform. In tests, the standard deviation of the removal rate across the wafer diameter was reduced to approximately 10.2%.

In addition to the embodiments described with reference to FIGURES 3-11, other pad shapes are possible that will also reduce the amount of pad material along the pad outer edge, e.g., star shapes, wheel spoke shapes, triangles, etc. Example shapes are shown in FIGURES 11A-11H. FIGURE 11A shows a "concentric square" buffing pad (*i.e.*, concentric with the buff head). FIGURE 11B shows a "concentric square with clipped corners" buffing pad similar to that shown in FIGURE 9. FIGURE 11C shows a "offset square" buffing pad (*i.e.*, offset with respect to the axis of rotation of the buff head). FIGURE 11D shows an "offset circular" buffing pad where the buffing pad is smaller than the buff head and is tangent at one point so that pure rotation of the buff head produces an orbital type of motion of the pad.

FIGURE 11E shows a "cross" buffing pad. FIGURE 11F shows a "scalloped cross" buffing pad. FIGURE 11G shows a "modified cross" buffing pad. FIGURE 11H shows a concentric circular buffing pad with a diameter smaller than that of the buff head. The actual removal rate profile for these configurations tend to vary. These different removal rate profiles can be optimal for a particular application. For example, the polishing process performed before the buffing process may result in a center fast or edge fast removal rate profile. An appropriate buffing unit configuration, including buffing pad shape, can be determined to compensate for the resulting topography after the primary polishing process.

While the preferred embodiment of the invention has been illustrated and described, it will be appreciated that various changes can be made therein without departing from the spirit and scope of the invention. For example, the buff pad may include grooves or slurry holes. Further, the present invention may be applied to other, more primary, processes in which a rotating head is pressed to a circular wafer for the purpose of removing portions of the wafer surface. In this regard, the term "buff" pad and "buffing" as used herein are generically defined to mean a material removing article including a primary polish step.

In another preferred embodiment of the invention, the planarization process is improved by allowing for removal of a material layer, preferably a barrier layer, on a buff station rather than on a primary polishing station. Unlike conventional CMP processes, this invention removes the interaction between multiple slurries used on the primary polishing station and also reduces the frequency of the need for conditioning the primary polish pad between removal steps. Also, removal of material from the wafer on the buff station occurs at a lower, more controlled rate than material removal on the primary polish pad. This lessens the amount of dishing that occurs at the plug and via areas. This invention thus reduces the amount of time necessary for processing as well as enhances the quality of planarization of the wafer surface.

The subject matter of the present invention is particularly suited for use in connection with Chemical Mechanical Planarization ("CMP") of substrates or semiconductor wafers. As a result, an exemplary embodiment of the present invention is described in that context. It should be recognized, however, that such description is not intended as a limitation on the use or applicability of the present invention, but is instead provided to enable a complete description of an exemplary embodiment. For example, the substrate being subjected to CMP may comprise a workpiece other than a silicon wafer, such as a flat panel display, a magnetic computer memory disc, a read-write head, or the like.

One exemplary method for planarizing a front surface of a wafer 12 in accordance with the present invention will now be described with respect to FIGURES 12 and 15. FIGURE 12h illustrates a typical semiconductor device. The wafer 12 has a well region 102 underlying an interlevel dielectric (ILD) layer 104 as shown in figure 12a. The first ILD layer 104 may be formed of silicon dioxide, but may also be formed of other dielectric materials such as silicon nitride, as well as other materials having a low dielectric constant, including fluorinated silicon dioxide or organic polymers. After formation of the first ILD layer 104, the layer 104 is etched to form an opening 103 (FIGURE 12b) that is coated with a barrier layer 118 (FIGURE 12c). The barrier layer 118 may be comprised of Ta, Ti, TiN, or a combination of the above, and may comprise a thickness of approximately 100-600 angstroms. This barrier layer 118 is used to improve adhesion of the metal 116 and to provide a barrier to prevent unwanted diffusion of the metal 116 into the dielectric 104. After the barrier layer 118 is deposited in the etchings and on the dielectric 104, a layer of plug metal 116, typically copper or tungsten is deposited over the barrier layer 118, as shown in FIGURE 12d. At this stage, the wafer is loaded in a primary polish station, such as shown in FIGURE 14, and pressed against the top surface of a primary polish pad (step 1501). The primary polish pad and/or carrier is then rotated (step 1502), thereby performing CMP on the plug metal 116 at the primary polish station 401 and primary polish pad 404, in the presence of slurry 405. The chemical slurry 405 is generally comprised of a polishing agent, such as alumina or silica, which is used as an abrasive material. Additionally, the slurry 405 may contain selected chemicals to etch or oxidize selected surfaces of the wafer 12 to prepare them for removal by the abrasive.

An endpoint detection system 407 (FIGURE 14) is used to determine the point at which the metal layer has been substantially removed from the wafer 12 surface, thereby exposing a barrier layer 118 (step 1503). Such a system 407 might be comprised of motor current detection, infra red based temperature change detection, or optical sampling techniques such as white light, infra red, or laser. When the plug metal 116 has been planarized to the point where the underlying barrier layer 118 becomes exposed (FIGURE 12e), the wafer 12 is transferred to the buff station 10 shown in FIGURE 13 (step 1504).

At the buff station 10, the polishing of the barrier layer 118 is commenced using a second slurry 23 from a slurry delivery system 24. This slurry delivery system 24 may comprise an apparatus capable of delivering one or more slurries 23, separately or in combination. The slurries 23 may comprise an abrasive suspension separately or in conjunction with an acid, base, aqueous solution, or water. Therefore, the slurry composition

may be altered or diluted between the step of barrier layer 118 removal and the step of buffing the wafer 12 surface. This second slurry 23 is preferably less chemically corrosive to the plug metal 116 and contains fewer abrasive particles.

5 The barrier layer 118 is then substantially removed (Figure 12f) from the wafer surface (step 1505). Metalized contacts 106 are thus embedded in the ILD layer 104. After the wafer 12 is transferred from the primary polish station 401 to the buff station 10, another wafer may be loaded in the primary polish station 401 for CMP removal of the plug metal 116, thus improving throughput.

10 The preferred rotation speed of the buff head 14 with attached buff pad 20 is approximately 350 rpm. The lower platen 16 and attached pad 21 are preferably rotated at approximately 300 rpm. An example of a pad used on the buff station is Politex Sureme™ by Rodell Corporation, with offices in Phoenix, Arizona. These pads are typically comprised of a polyurethane or other suitable material. The pressure exerted on the wafer 12 by the buffer system during polishing may be approximately 3 psi. Typical removal rates of the barrier layer 15 118 on the buff station 10 using the above disclosed process are approximately 1000-3000 angstroms/minute. Because a typical barrier layer 118 is approximately 200-1000 angstroms thick, this step will last for approximately 4 - 60 seconds, depending on the removal rate and the barrier layer 118 thickness.

20 Using a detection system on the buff station, the point at which the barrier layer 118 has been substantially removed from the wafer surface is detected (step 1506). Various techniques may be employed to determine endpoint, including a variety of optical, motor current, laser, or infra-red techniques. Optical sensors based on optical interference or ellipsometry are two examples of possible means for determining endpoint. Examples of optical endpoint detection systems may be seen in U.S. Patents No. 5,972,162 and 6,106,662, and are hereby incorporated 25 by reference. An example of a motor current method may be seen in U.S. Patent No. 5,667,629 and is hereby incorporated by reference. After the barrier layer 118 has been substantially removed, the buff station parameters, including pressure, speed, and buff slurry 23, may be modified (step 1507) and the buff station 10 is then used to buff the wafer 12 (step 1508).

30 By utilizing this invention and removing the barrier layer at the buff station 10, the first polish pad 404 may be set up with a slurry 405 which polishes the metal layer 116 and the buff station 10 may be set up with a different slurry 23 to more effectively polish the barrier layer 118. Thus, the need for changing slurry compositions on the primary polishing station 401 is

removed. After barrier layer 118 removal, the parameters of the buff station 10 may then be changed to buff the wafer surface 12.

The method of the present invention allows both the polishing slurry and the polishing pad configuration to be different for the metal layer 118 (primary polishing station 401) removal versus the barrier layer 118 (buff station 10) removal. Different polishing pads and slurries may be beneficial for metal CMP than for barrier layer removal. For example, a more abrasive pad may be used at the primary polish station 401 to allow for faster removal of bulk metal material. In addition, the planarization process is improved by minimizing metal dishing and field oxide erosion on the wafer surface because the buff station 10 may remove material from the wafer 12 surface in a more controlled manner.

In the preferred embodiment of the present invention, the same pads are used for both barrier layer 118 removal and buffing at the buff station 10. The same slurry may also be used, but diluted with water between barrier layer 118 removal and buffing steps.

Another advantage to removal of the barrier layer 118 on the buff station 10 is the ability to begin polishing a second wafer while the first wafer 12 is at the buff station 10. The steps in such a process cycle may include loading a wafer 12 in a carrier 403 at a primary polishing station 401, where a metal layer 116 is removed. The barrier layer 118 may then be removed on the buff station 10, followed by a buffing process. The wafer 12 may then be unloaded from the buff station 10. At the point in the process in which the wafer 12 has been transferred to the buff station 10, pad conditioning on the primary polishing station 401 may immediately commence if necessary. A second wafer's metal layer may then be polished on the primary polishing station 401 while the first wafer 12 is at the buff station 10 which improves machine throughput. Additionally, by removing the barrier layer 118 on the buff station 10, the time the wafer 12 spends on the primary polishing station 401 is reduced. This shorter polish time results in shorter polish pad conditioning time, which further increases throughput.

While embodiments herein have been described for use with copper, it is well understood that the present invention may be utilized to perform CMP on other metals, such as tungsten or aluminum. In such cases, the chemical oxidizer and the abrasive slurry component may change depending on the particular metallurgy, as is well known in the art. That is, conventional CMP slurries may be utilized in connection with tungsten, copper, or aluminum. Further, the present invention may be beneficially utilized in, for example, a Shallow Trench Isolation (STI) polishing process. In an STI process in accordance with the present invention, a

dielectric layer is removed from the wafer surface on a conventional CMP polish station, leaving the underlying barrier layer exposed and substantially intact. The wafer is then moved from the CMP polish station to the buff station, where the barrier layer is subsequently removed.

5 The foregoing description of the invention is not intended to be exhaustive or to limit the invention to the precise form disclosed. Obviously, many modifications and variations will be apparent to practitioners skilled in this art. It is possible that the invention may be practiced to remove materials other than metal from the surface of a wafer. The embodiment was chosen and described in order to best explain the principles of the invention and its practical application, thereby enabling others skilled in the art to understand the invention for various  
10 embodiments and with various modifications as are suited for the particular use contemplated. It is intended that the scope of the invention be defined by the claims appended hereto and their equivalents.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208